

The **NOMAD POWER 12/24 V** is a super-powerful lithium-based power source that combines three functions:

- **Booster for 12 V vehicles** (cars, SUVs, commercial vehicles, tractors, boats) and **24 V vehicles** (buses, heavy goods vehicles, construction machinery).
- **Power bank for powering or charging all electronic devices.**
- **Emergency light/torch..**

## PROFESSIONAL LITHIUM BATTERY BOOSTER

- Equipped with a **high-performance lithium battery**, the NP 12/24 V delivers an impressive 1900 A of current, while remaining ultra-compact in size.
- Its **exceptional starting power** means that any vehicle equipped with a lead-acid battery (liquid, gel, AGM, Start&Stop), both 12V and 24V, can be started in a matter of seconds, even if the battery is discharged.

⚠ do not start Lithium LiFePO4 batteries with this booster, as the voltages are not compatible.

## SAFE STARTING

The **NOMAD POWER 12/24 V** protects both the battery and the electronic systems in your vehicle:

- Anti-spark technology,
- Short-circuit protection,
- Protection against polarity reversal.
- Excessive starting current protection,
- Thermal overload protection for the booster.

## MOBILE ENERGY SOURCE

The massive 8.4 Ah battery capacity offers convenience and reassurance for those who need to stay connected on the move. The **two USB-A 5 V - 2.4 A** ports are ideal for charging smartphones, tablets, smartwatches, and other electronic devices.



## EMERGENCY LIGHT

Single-LED lamp with 3 lighting modes: normal, strobe, SOS.

## COMPACT FORMAT

**Lightweight** (4.4 kg) and **compact**, it easily fits in a breakdown vehicle or workshop.



|  |                        |
|--|------------------------|
|   | <b>12 V</b> 5 > 180 Ah |
|  | <b>24 V</b> > 240 Ah   |

### Charging LED



### Supplied with charger



Charging unit

| STARTING          |                    |             |                       | INPUT / OUTPUT |        |              |  | POWER BANK           | LED | DIMENSIONS                         |                       |     |     |
|-------------------|--------------------|-------------|-----------------------|----------------|--------|--------------|--|----------------------|-----|------------------------------------|-----------------------|-----|-----|
| Lithium           |                    |             | START PETROL & DIESEL | I              |        |              | INPUT  | OUTPUT               | ☑   | ☀                                  | cm                    | kg  | m   |
| Capacity per cell | Type               | Full charge |                       | 1 V/C          | 0 V/C  | Peak Battery |  |                      |     |                                    |                       |     |     |
| 8.4 Ah<br>218 Wh  | LiCoO <sub>2</sub> | 4 h         | 12 / 24 V             | 1900 A         | 3000 A | 4000 A       | 2   JACK DC 05.5: 29V - 5 A<br>SB-C: 5V/2A 9V/2A | 2   USB-A 5V - 2.4 A | ☑   | 3 modes:<br>Light<br>SOS<br>Strobe | 29.5 x 24.5<br>x 17.5 | 4.4 | 0.7 |